

# **SDN** Bus Booster

Part #1049436

#### **OVERVIEW**

The SDN Bus Booster is a Somfy Digital Network™ (SDN) component that provides 24V power to the bus line. It can act as an in-line power extender or provide stand-alone power to a segment. It can be connected anywhere on the bus without the need for splitters or hubs. The SDN Bus Booster is plenum-rated and enables flexible large-scale designs and convenient installation.

#### **SOMFY DIGITAL NETWORK SYSTEM OVERVIEW**

Somfy Digital Network (SDN) is Somfy's intelligent wired shading network. An SDN system is comprised of bus distribution devices that create a network for user interfaces, motorized applications, and integration devices. SDN is scalable and suitable for both small and large projects. The same components are used whether an SDN system remains stand-alone, is integrated into third-party automation systems, or is paired with Somfy's animeo IP automated total solar management system.



# **TECHNICAL SPECIFICATIONS**

Input	120V, 0.75A 230V, 0.5A 277V, 0.375A	
Output	24V, 1A	
Material	Steel Enclosure	
Dimensions	4 in. L x 4 in. W x 1.5 in. H (10.16cm L x 10.16cm W x 13.81cm H)	
Operating Temperature Range	Ambient temperature	
Shipping Weight	1.5 lbs	
Indoor use only		
Plenum-rated		
c UL us		

#### **FEATURES SUMMARY**


- In-line segment extender
- No outlet required (connected directly to AC power wires)
- Standard size junction box
- Protects system components from miswire
- Uses RJ45 connectors

# WHAT'S IN THE BOX

- SDN Bus Booster
- Instructions

#### **CABLE PINOUTS**

SDN Pinout ANSI/TIA/EIA 568-B Standard



#### **CONNECTIONS AND INDICATORS**


	ELEMENT	FUNCTION
1	SDN Bus Input	Input for bus signals
2	SDN Bus Output	Output for bus signals


LED Indicators				
Label	Element	Function ON	Function Off	
1	Bus In Activity	Bus activity incoming	No bus activity incoming	
Р	24V Power	Outgoing 24V power	No outgoing bus power	
0	Bus Out Activity	Bus activity outgoing	No bus activity outgoing	




# **SDN** Bus Booster

# **DIMENSIONS**







### **BEST WIRING PRACTICES**

The diagram below is meant for illustrative purposes to show the connections from product to product. This device could be used in other configurations than shown below. For specification information on individual products see related product information. Follow all SDN wiring standards for distance limitations.

